

1. For each of following systems,  $y[n]$  denotes the output and  $x[n]$  the input. For each system, determine whether the specified input-output relationship is linear and/or shift-invariant.

(a)  $y[n] = 4x[n] + 1$

(b)  $y[n] = x[n] \sin\left(\frac{2\pi}{5}n + \frac{\pi}{8}\right)$

(c)  $y[n] = (x[n])^2$

(d)  $y[n] = \sum_{m=n-N}^n x[m]$

2. Consider the sequence

$$x[n] = \begin{cases} a^n & n \geq n_0 \\ 0 & n < n_0 \end{cases}$$

- (a) Determine the z-transform of  $x[n]$ .
- (b) Determine the Fourier transform of  $x[n]$ . Under what conditions does the Fourier transform exist?

3. Consider the first-order system, causal system,

$$y[n] = \alpha y[n-1] + x[n]$$

- (a) Find the system function,  $H[z]$ , for this system.
- (b) Find the impulse response of this system.
- (c) For what values of  $\alpha$  will the system be stable?
- (d) Assume that the input is obtained by sampling with period  $T$ . Determine the value of  $\alpha$  such that

$$h[n] < e^{-1} \quad \text{for} \quad nT < 4 \text{ msec}$$

i.e., find the value of  $\alpha$  that gives a time constant of 4msec.

4. A speech signal is sampled at a rate of 10000 samples/sec(10 kHz). A segment of length 1024 samples is selected and the 1024-point DFT is computed.
- (a) What is the time duration of segment of speech?
- (b) What is the frequency resolution (spacing in Hz) between the DFT values?
- (c) How do your answers to parts (a) and (b) change if we compute the 1024-point DFT of 512 samples of the speech signal. (The 512 samples would be augmented with 512 zero samples before the transform was computed.)